

UPS Polaris RT-A 3000

HIGH POWER DENSITY
RACK-TOWER 2-IN-1 TRUE
DOUBLE CONVERSION
ONLINE UPS

- DSP Control
- 0.9 Output Power Factor
- Wide Input Range
- High Efficiency Mode(ECO)
- Frequency Converter Mode
- Compact Design
- Power Management Software
- Multiple Communication Ports
- Optional SNMP & Relay Cards
- Temperature Compensation
- PDU(for 6-10KVA)
- 1+1 Parallel for 6-10KVA



UPS Polaris
RT-A 3000

MODELO		3KVA
PHASE		SINGLE PHASE WITH GROUND
CAPACITY (VA/WALTS)		3000VA/2700W
INPUT		
NOMINAL VOLTAGE		200/208/220/230/240VAC
OPERATING VOLTAGE RANGE	LOW LINE TRANSFER	160VAC±5% @100%-80% LOAD; 140VAC±5% @80%-70% LOAD; 120VAC±5% @70%-60% LOAD; 110VAC±5% @60%-0% LOAD; (AMBIENT TEMP. <35°C)
	LOW LINE COMEBACK	175VAC±5% @100%-80% LOAD; 155VAC±5% @80%-70% LOAD; 135VAC±5% @70%-60% LOAD; 125VAC±5% @60%-0% LOAD; (AMBIENT TEMP. <35°C)
	HIGH LINE TRANSFER	300VAC±5%
	HIGH LINE COMEBACK	290VAC±5%
OPERATING FREQUENCY RANGE		40-70HZ

UPS Polaris
RT-A 3000

POWER FACTOR	0,99@100% LOAD (NOMINAL INPUT VOLTAGE)	
BYPASS VOLTAGE RANGE	<p>BYPASS HIGH VOLTAGE POINT 230-264: SETTING THE HIGH VOLTAGE POINT IN LCD FROM 230VAC (DEFAULT: 264 VAC)</p> <p>BYPASS LOW VOLTAGE POINT 170-220: SETTING THE LOW VOLTAGE POINT IN LCD FROM 170VAC TO 220VAC (DEFAULT: 170 VAC)</p>	
GENERATOR INPUT	SUPPORT	
OUTPUT		
OUTPUT VOLTAGE	220/208/220/230/240VAC	
POWER FACTOR	0,9	
VOLTAGE REGULATION	±1%	
FREQUENCY	LINE MODE (SYNCHRONIZED RANGE)	47-53HZ OR 57-63 HZ
	BAT. MODE	(50/60±0,1) HZ

UPS Polaris
RT-A 3000

CREST FACTOR		3:1
HARMONIC DISTORTION (THDC)		≤3% THD WITH LINEAR LOAD ≤6% THD WITH NON LINEAR LOAD
WAVEFORM		PURE SINEWAVE
TRANSFER TIME	AC MODE <-> BALT. MODE	ZERO
	INVERTER <-> BYPASS	4MS (TYPICAL)
EFFICIENCY		92% (AC MODE) 90% (DC MODE)
BATTERY		
BATTERY TYPE		12V9AH
NUMBERS		6

UPS Polaris
RT-A 3000

BACKUP TIME	LONG RUN UNIT DEPENDS ON THE CAPACITY OF EXTERNAL BATTERIES
TYPICAL RECHARGE TIME (STANDARD MODLE)	4 HOURS RECOVER TO 90% CAPACITY (TYPICAL)
CHARGING VOLTAGE	82.1 VDC \pm 1%
CHARGE CURRENT	1A
SYSTEM FEATURES	
OVERLOAD @35°C	<p>AMBIENT TEMP. <35°C</p> <p>105%-110%: UPS TRANSFER TO BYPASS AFTER 10 MINUTES WHEN THE UTILITY IS NORMAL.</p> <p>110%-130%: UPS TRANSFER TO BYPASS AFTER 1 MINUTE WHEN THE UTILITY IS NORMAL</p> <p>130%-150%: UPS TRANSFER TO BYPASS AFTER 5 SECONDS WHEN THE UTILITY IS NORMAL</p> <p>>150%: UPS TRANSFER TO BYPASS IMMEDIATELY WHEN THE UTILITY IS NORMAL</p> <p>35°C<AMBIENT TEMP. <40°C</p> <p>105%-110%: UPS TRANSFER TO BYPASS AFTER 1 MINUTE WHEN THE UTILITY IS NORMAL</p> <p>110%-130%: UPS TRANSFER TO BYPASS AFTER 5 SECONDS WHEN THE UTILITY IS NORMAL</p> <p>>130%: UPS TRANSFER TO BYPASS IMMEDIATELY WHEN THE UTILITY IS NORMAL</p>

UPS Polaris
RT-A 3000

SHORT CIRCUIT	HOLD WHOTE SYSTEM
OVERHEAT	LINE MODE: SWITCH TO BYPASS; BACKUP MODE: SHUT DOWN UPS IMMEDIATELY
LOW BATTERY VOLTAGE	ALARM AND SWITCH OFF
EPO (OPTIONAL)	SHUT DOWN UPS IMMEDIATELY
AUDIBLE & VISUAL ALARMS	LINE FAILURE, BATTERY LOW, OVERLOAD, SYSTEM FAULT
COMUINICATION INTERFACE	USB (OR RS232), SNMPCARD (OPTIONAL), RELATY CARD (OPTIONAL)
ENVIRONMENTAL	
OPERATING TEMPERATURE	0°C = 40°C
STORAGE TEMPERATURE	-25°C = 55°C
HUMIDITY RANGE	20-90 % RH @ 0-40°C (NON-CONDENSING)
ALTITUDE	<1500M
NOISE LEVEL	LESS THAN 50DBA AT 1 METER

UPS Polaris
RT-A 3000

PHYSICAL	
DIMENSION WXHXD (MM)	440*720* 86,5
NET WEIGHT (KG)	28,6
STANDARDS	
SAFETY	IEC/EN62040-1, IEC/EN60950-1
EMC	IEC61000-4-5, IEC61000-4-6, IEC61000-4-8

*DERATE TO 80% OF CAPACITY WHEN THE OUTPUT VOLTAGE IS ADJUSTED TO 200/208VAC.

**PRODUCT SPECIFICATIONS ARE SUBJECT TO CHANGE WITHOUT FURTHER NOTICE.

POLARIS
Energy Systems

Zapiola 4248 3º B - Saavedra (C1429AOD)
Ciudad Autónoma de Buenos Aires
Argentina

info@upspolaris.com
(5411) 5235-UPSS (8777)